



SENSOR DE MOVIMIENTO

APLIQUE LED AVANZADO CON SENSOR IR

ADIÓS INTERRUPTORES.

El sensor integrado dentro del aplique avanzado confiere gran comodidad y seguridad a la instalación. Un encendido automático por movimiento asegura que la luz queda encendida cuando es necesaria, sin el inconveniente de apagados indeseados como ocurre con los temporizadores pero también asegura que no queda consumiendo energía cuando no está en uso. Versión emergencia también disponible.


GOODBYE SWITCHES.

The integrated sensor inside the advanced fixture provides great comfort and safety to the installation. An automatic start by movement ensures that the light remains on when it is needed, without the inconvenience of unwanted shutdowns as occurs with timers but also ensures that it is not consuming power when it is not in use. Emergency version also available.

Modelo Model	LSL0330S	LSL0330ES	LSL0630S	LSL0630ES
Sensor Sensor	Sí (IR)	Sí (IR)	Sí (IR)	Sí (IR)
Tensión entrada Input voltage	230V	230V	230V	230V
Frecuencia Frequency	50Hz	50Hz	50Hz	50Hz
Flujo lumínico Lumen	650Lm	680Lm	1200Lm	1200Lm
Flujo lumínico/emergencia Lumen/emergency	-	300Lm	-	300Lm
Potencia Power	6W	8W	13W	15W
Potencia emergencia Emergency power	-	3W	-	3W
Temperatura de color Color temperature	4000K □	4000K □	4000K □	4000K □
Duración de la batería Battery life	-	2h	-	2h
Dimensiones Size	375x50x50mm		605x50x50mm	
Material base Base material	Aluminio / Aluminum			
Material difusor Diffuser material	Plástico translúcido / Translucent plastic			
Material tapa Cover material	Plástico plata / Silver plastic			
Ángulo Angle	120°	120°	120°	120°
IP	40	40	40	40



LSL0330S
LSL0330ES



LSL0630S
LSL0630ES



Videos demostrativos:
www.pritec.com/videos

